



**NEOi 809**  
**Quick Reference**  
**for MMS / GPRS /**  
**Wap settings /**  
**Einstellungen**

## Example : E-Plus (Germany) MMS settings

### Instructions

#### MMS Data Account

- Navigate to – Menu > Services > Data Account > GPRS
- Select “**Account 1**”
- Edit the Account name from “Account 1” to “**eplus MMS**”
- Press “Option > Done”
- Edit APN to say “**mms.eplus.de**”
- Edit User Name to “**mms**”
- Edit Password to “**eplus**”
- Set Authority. Type to “Normal”
- Press “DONE”
- Press “Yes” to “Save” the settings.

#### Set Up MMS Account

- Navigate to - Menu > Messages > MMS > Message Settings > Server Profile
- Select “Profile 1” and press “OK”
- Select “Edit Profile”
- Rename “Profile 1” to “**ewap MMS**”
- Change Home Page Address to <http://mms/eplus>
  
- Go to “Data Account” and press “Select”, on the next screen, select “GPRS” and press “OK”. From the list navigate to the account named “eplus MMS” and select “OK”
- Connection Type Select “HTTP” and press “OK” and on the next screen type in the Proxy Address “**212.023.097.153**” and the Proxy Port “**8080**”.
- Press “OK”
- User name “**mms**”
- Password “**eplus**”
- Press “Done”

- Press "Yes" to save the Settings.

*Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to eplus MMS.*

**Example: Vodafone MMS settings**

**Access Point Name: wap.vodafone.co.uk**

**Username: wap**

**Password: wap**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP (proxy) address: 212.183.137.012**

**Session mode: Permanent**

**MMS Message (Relay) Server URL:**

<http://mms.vodafone.co.uk/servlets/mms/>

**Instructions**

**MMS Data Account**

- Navigate to – Menu > Services > Data Account > GPRS
- Select "Account 1"
- Edit the Account name from "Account 1" to "Voda MMS"
- Press "Option > Done"
- Edit APN to say "wap.vodafone.co.uk"
- Edit User Name to say "wap"
- Edit Password to "wap"
- Set Authority. Type to "Normal"
- Press " DONE"
- Press "Yes" to "Save" the settings.

**Set Up MMS Account**

- Navigate to - Menu > Messages > MMS > Message Settings > Server Profile

Select "Profile 1" and press "OK"

Select "Edit Profile"

Rename "Profile 1" to "Voda MMS"

Change Home Page Address to

<http://mms.vodafone.co.uk/servlets/mms/>

Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".

From the list navigate to the account named "Voda MMS" and select "OK"

Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy

Address "212.182.137.012" and the Proxy Port "8080".

- Press "OK"
- User name "wap"
- Password "wap"
- Press "Done"
- Press "Yes" to save the Settings.

***Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Voda MMS.***

**Nun, wenn Sie Ihren Service Provider anrufen und sich entsprechend die Settings fuer (Vodafone Deutschland) den Service Provider geben lassen , koennen sie zumindest MMS empfangen.**

**Sollten sie auf auslands Reise gehen, wie in England , so funktioniert es dort , wenn mann das Profile so einstellt.**

**Anbei Einstellungen fuer weitere Service Provier im In-Ausland:**

#### **ETISALAT MMS Data Account**

- Navigate to "Services"
- Go To "Data Account"
- Go To "GPRS"
- Select "Account 1"
- Edit the Account name from "Account 1" to " Etisalat MMS"
- Press "Done"
- Edit APN to say "mms"
- Edit User Name to say " mms"
- Edit Password to " mms"
- Set Authority. Type to "Normal"
- Press " DONE"
- Press "Yes" to "Save" the settings.

#### **Set Up MMS Account**

- Navigate to "Messages"
- Select "MMS"
- Select " Message Settings"
- Select "Server Profile"
- Select "Profile 1" and press "OK"
- Select "Edit Profile"
- Rename "Profile 1" to "MMS"
- Change Home Page Address to "http://mms/servlets/mms"
- Date Account Select "GPRS" Press "OK" then "Select" Etisalat MMS Press "OK"
- Connection Type Select "HTTP"
- Press "OK"
- Proxy Address "010.012.000.030"
- Press "OK"
- Proxy Port "8080"

- Press "OK"
- User name "mms"
- Password "mms"
- Press "Done"
- Press "Yes" to save the Settings.

Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Etisalat MMS.

#### **Du MMS Data Account**

- Navigate to – Menu > Services > Data Account > GPRS
- Select "Account 1"
- Edit the Account name from "Account 1" to " Du MMS"
- Press "Option > Done"
- Edit APN to say "mms"
- Edit User Name to say "(Leave Blank)"
- Edit Password to "(Leave Blank)"
- Set Authority. Type to "Normal"
- Press " DONE"
- Press "Yes" to "Save" the settings.

#### **Set Up MMS Account**

- Navigate to - Menu > Messages > MMS > Message Settings > Server Profile
  - Select "Profile 1" and press "OK"
  - Select "Edit Profile"
  - Rename "Profile 1" to "Du MMS"
  - Change Home Page Address to <http://mms.du.ae>
  - Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".
- From the list navigate to the account named "Du MMS" and select "OK"
- Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy Address "010.019.018.004" and the Proxy Port "9201".
  - Press "OK"
  - User name "(Leave Blank)"
  - Password "(Leave Blank)"
  - Press "Done"
  - Press "Yes" to save the Settings.
- Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Du MMS.

#### **Orange MMS settings**

Access Point Name: orangemms

Username: Orange

Password: Multimedia

Authentication: Normal

Data bearer: GPRS

**Gateway IP (proxy) address: 192.168.224.10**  
**Port: 9201 (some users have reported 8080 (WAP) works if 9201 doesn't)**

**Session mode: Permanent**

**MMS Message (Relay) Server URL <http://mms.orange.co.uk/>**

#### **Instructions**

##### **MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " Orange MMS"**
- **Press "Option > Done"**
- **Edit APN to say "orangemms"**
- **Edit User Name to say "orange"**
- **Edit Password to "multimedia"**
- **Set Authority. Type to "Normal"**
- **Press " DONE"**
- **Press "Yes" to "Save" the settings.**

##### **Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings > Server Profile**
- **Select "Profile 1" and press "OK"**
- **Select "Edit Profile"**
- **Rename "Profile 1" to "Orange MMS"**
- **Change Home Page Address to <http://mms.orange.co.uk/>**
- **Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".**

**From the list navigate to the account named "Orange MMS" and select "OK"**

- **Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy Address "192.168.224.010" and the Proxy Port "8080".**

- **Press "OK"**
- **User name "orange"**
- **Password "multimedia"**
- **Press "Done"**
- **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Orange MMS.**

#### **O2 MMS settings**

**Access point name: wap.o2.co.uk (contract customers) or payandgo.o2.co.uk (pay-as-you-go customers)**

**Username: o2wap (contract customers) or payandgo (pay-as-you-go customers)**

**Password: password**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP (proxy) address: 193.113.200.195**

**Session mode: Permanent**

**Port number: 8080 or 9201**

**URL address: http://mmsc.mms.o2.co.uk:8002**

**Instructions**

**MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " O2 MMS"**
- **Press "Option > Done"**
- **Edit APN to say "wap.o2.co.uk"**
- **Edit User Name to say "o2wap" for contract customers and "payandgo.o2.uk" for Pay-as-yougo customers.**

- **Edit Password to "password"**

- **Set Authority. Type to "Normal"**

- **Press " DONE"**

- **Press "Yes" to "Save" the settings.**

**Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings > Server Profile**

- **Select "Profile 1" and press "OK"**

- **Select "Edit Profile"**

- **Rename "Profile 1" to "O2 MMS"**

- **Change Home Page Address to http://mmsc.mms.o2.co.uk:8002**

- **Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".**

**From the list navigate to the account named "O2 MMS" and select "OK"**

- **Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy**

**Address "193.113.200.195" and the Proxy Port "8080" or "9201".**

- **Press "OK"**

- **User name "o2wap"**

- **Password "password"**

- **Press "Done"**

- **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or**

**Activated Profile is set to O2 MMS.**

### **Vodafone MMS settings**

**Access Point Name: wap.vodafone.co.uk**

**Username: wap**

**Password: wap**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP (proxy) address: 212.183.137.012**

**Session mode: Permanent**

**MMS Message (Relay) Server URL:**

**<http://mms.vodafone.co.uk/servlets/mms/>**

**Instructions**

**MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to "Voda MMS"**
- **Press "Option > Done"**
- **Edit APN to say "wap.vodafone.co.uk"**
- **Edit User Name to say "wap"**
- **Edit Password to "wap"**
- **Set Authority. Type to "Normal"**
- **Press "DONE"**
- **Press "Yes" to "Save" the settings.**

**Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings >**

**Server Profile**

- **Select "Profile 1" and press "OK"**
- **Select "Edit Profile"**
- **Rename "Profile 1" to "Voda MMS"**
- **Change Home Page Address to**  
**<http://mms.vodafone.co.uk/servlets/mms/>**
- **Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".**

**From the list navigate to the account named "Voda MMS" and select "OK"**

- **Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy**

**Address "212.182.137.012" and the Proxy Port "8080".**

- **Press "OK"**
- **User name "wap"**
- **Password "wap"**
- **Press "Done"**
- **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Voda MMS.**

**T-Mobile (UK) MMS settings**

**Fuer T-Mobile Deutschland, gehen Sie bitte zur T-Mobile Deutschland Webseite.**

**Access Point Name: general.t-mobile.uk**

**Username: user**

**Password: one2one**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP (proxy) address: 149.254.211.10 (also 149.254.201.135)**

**Session mode: Permanent**

**MMS Message (Relay) Server URL: <http://mmsc.t-mobile.co.uk:8002/>**

#### **Instructions**

##### **MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " T MMS"**
- **Press "Option > Done"**
- **Edit APN to say "general.t-mobile.uk"**
- **Edit User Name to say "user"**
- **Edit Password to "one2one"**
- **Set Authority. Type to "Normal"**
- **Press " DONE"**
- **Press "Yes" to "Save" the settings.**

##### **Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings >**

##### **Server Profile**

- **Select "Profile 1" and press "OK"**
  - **Select "Edit Profile"**
  - **Rename "Profile 1" to "T MMS"**
  - **Change Home Page Address to <http://mmsc.t-mobile.co.uk:8002/>**
  - **Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".**
- From the list navigate to the account named "T MMS" and select "OK"**
- **Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy Address "149.254.211.010" or "149.254.201.135" and the Proxy Port "8080".**
  - **Press "OK"**
  - **User name "user"**
  - **Password "one2one"**
  - **Press "Done"**
  - **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to T MMS.**

#### **Virgin MMS settings**

**Note: Virgin must enable MMS for your account. Contact Virgin Customer Services**

**Access Point Name: [goto.virginmobile.uk](http://goto.virginmobile.uk)**

**Username: user**

**Password: (leave blank)**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP (proxy) address: 193.030.166.001**

**Port: 8080**

**Session mode: Permanent**  
**MMS Message (Relay) Server URL**  
**http://mms.virginmobile.co.uk:8002**

**Instructions**

**MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " Virgin MMS"**
- **Press "Option > Done"**
- **Edit APN to say "goto.virginmobile.uk"**
- **Edit User Name to say "user"**
- **Edit Password to "(leave Blank)"**
- **Set Authority. Type to "Normal"**
- **Press " DONE"**
- **Press "Yes" to "Save" the settings.**

**Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings >**

**Server Profile**

- **Select "Profile 1" and press "OK"**
- **Select "Edit Profile"**
- **Rename "Profile 1" to "Virgin MMS"**
- **Change Home Page Address to**  
**http://mms.virginmobile.co.uk:8002**
- **Go to "Data Account" and press "Select", on the next screen,**  
**select "GPRS" and press "OK".**

**From the list navigate to the account named "Virgin MMS" and**  
**select "OK"**

- **Connection Type Select "HTTP" and press "OK" and on the next**  
**screen type in the Proxy**  
**Address "193.030.166.001" and the Proxy Port "8080".**
- **Press "OK"**
- **User name "user"**
- **Password "(Leave Blank)"**
- **Press "Done"**
- **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings >**  
**Server Profile, the selected profile or**  
**Activated Profile is set to Virgin MMS.**

**Tesco Mobile MMS settings**

**Access point name: prepay.tesco-mobile.com**

**Username: tescowap**

**Password: password**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP address: 193.113.200.195**

**Session mode: Permanent**

**URL address: http://mmsc.mms.o2.co.uk:8002**

**Instructions**

### **MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " Tesco MMS"**
- **Press "Option > Done"**
- **Edit APN to say "prepay.tesco-mobile.com"**
- **Edit User Name to say "tescowap"**
- **Edit Password to "password"**
- **Set Authority. Type to "Normal"**
- **Press " DONE"**
- **Press "Yes" to "Save" the settings.**

### **Set Up MMS Account**

- **Navigate to - Menu > Messages > MMS > Message Settings > Server Profile**
- **Select "Profile 1" and press "OK"**
- **Select "Edit Profile"**
- **Rename "Profile 1" to "Tesco MMS"**
- **Change Home Page Address to <http://mmsc.mms.o2.co.uk:8002>**
- **Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".**

**From the list navigate to the account named "Tesco MMS" and select "OK"**

- **Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy Address "193.113.200.195" and the Proxy Port "8080".**

- **Press "OK"**
- **User name "tescowap"**
- **Password "password"**
- **Press "Done"**
- **Press "Yes" to save the Settings.**

**Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to Tesco MMS.**

### **BT Mobile MMS settings**

**Access point name: mobile.bt.uk**

**Username: user**

**Password: btmms**

**Authentication: Normal**

**Data bearer: GPRS**

**Gateway IP address: 212.183.137.012 or 62.239.21.123**

**Session mode: Permanent**

**URL address: <http://mms.bt.com/servlets/mms> or**

**<http://mmsc.btmms.co.uk:8002>**

### **Instructions**

#### **MMS Data Account**

- **Navigate to – Menu > Services > Data Account > GPRS**
- **Select "Account 1"**
- **Edit the Account name from "Account 1" to " BT MMS"**

- Press "Option > Done"
  - Edit APN to say "mobile.bt.uk"
  - Edit User Name to say "user"
  - Edit Password to "btmms"
  - Set Authority. Type to "Normal"
  - Press " DONE"
  - Press "Yes" to "Save" the settings.
- Set Up MMS Account**
- Navigate to - Menu > Messages > MMS > Message Settings > Server Profile
  - Select "Profile 1" and press "OK"
  - Select "Edit Profile"
  - Rename "Profile 1" to "BT MMS"
  - Change Home Page Address to <http://mms.bt.com/servlets/mms> or <http://mmsc.btmms.co.uk:8002>
  - Go to "Data Account" and press "Select", on the next screen, select "GPRS" and press "OK".
- From the list navigate to the account named "BT MMS" and select "OK"
- Connection Type Select "HTTP" and press "OK" and on the next screen type in the Proxy Address "212.183.137.012" and the Proxy Port "8080".
  - Press "OK"
  - User name "user"
  - Password "btmms"
  - Press "Done"
  - Press "Yes" to save the Settings.
- Make sure that in Menu > Messages > MMS > Message Settings > Server Profile, the selected profile or Activated Profile is set to BT MMS.

## **SET UP Instructions Neoi 809 WAP**

To set up the WAP Browser on the 809 series of Phones please follow this [example for Starhub Singapore](#), but **substitute Carrier Specific Settings** with YOUR Carriers settings. **Please go to the WAP Homepage of your service provider for specific Data and settings.**

- 1.) From Menu go to SERVICES
- 2.) Enter
- 3.) Select WAP (2) >>> Enter
- 4.) Select SETTINGS (6) >>> Enter
- 5.) Select EDIT PROFILE (1)
- 6.) Select Profile 1...10 >>>Enter
- 7.) Select EDIT PROFILE (2) >>> Enter
- 8.) Follow Menu:

- a.) **Edit** Rename Profile to **YOUR Carriers Name** ( in this Example we use Starhub ) **Starhub**
- b.) **Edit** Insert Home Page Name <http://gee-select.starhubgee.com.sg/wap>
- c.) **Select** Enter Data Account **STARHUB GPRS** ( Please NOTE! You have to **set up FIRST your Carriers GPRS settings**, in the Phone's Service Menu!)
- d.) **Select** / Insert Connection Type **HTTP**
- e.) **Edit** Insert Username if required ( Note most SIM Card operators do not require a username anymore, as the SIM card code is the username)
- f.) **Edit** Insert Password if required

After Save go BACK

(1) Activate the appropriate Profile .... OK ... Yes ... **Done** ...Back

**Go to Browser Options**

- (1) Timeout **300**
- (2) Show Images **ON**  
OK ...Save... Yes ... Done

**Go to Service Message Settings**

- (3) Select **ON**

**Go to Clear Cache**

Clear Cache ... Yes ..Done...

**Go to Clear Cookies**

Clear Cookies .. YES .. Done

**Go to Trusted Certificates**

**Select the Certificate (1) or (2) which YOUR carrier recognizes !**

Go BACK ... to Internet Services Menu Screen

- (4) Enter Address

**Enter YOUR Carriers WAP Homepage**

Go to (1) Homepage and test Settings. **Make sure the GPRS Icon appears on the main screen (top). If the Icon does NOT appear then:**

- a.) You do not have a Data service Agreement with Your Carrier
- b.) You do have a Pre-paid SIM card, ALL pre-paid SIM Cards do NOT have Data services
- c.) You are Roaming, and the Roaming partner has no data Service agreement with your Home Carrier
- d.) You bought your Phone from a private shop, who has no contract with a carrier for pre-set services, or your home carrier allows only Data Services from sets bought in their official shop, with official pre settings.

**e.) Check your Phone's GPRS settings**

**NOTE:**

**In Your 809 Series settings for GPRS, under (2) GPRS, you MUST have 2 different settings:**

- (1) WAP settings**
- (2) MMS Settings**

**The following are the WAP, GPRS and MMS settings for China Mobile :**

**1. services ---- Data Account ---- GPRS 作如下配置**

**Choose Account1 to change:**

**Account name : CHINA MOBILE GPRS**

**APN : cmwap**

**2.**

**Services ---- WAP --- Settings ---- Edit Profile**

**Choose Profile1 to choose:**

**Rename Profile : china mobile**

**Homepage : <http://wap.monternet.com>**

**Data Account: CHINA MOBILE GPRS**

**Connection Type : HTTP**

**Proxy Address : 010.000.000.172**

**Proxy Port : 80**

**3.**

**MMS settings:**

**Message settings --- Server profile:**

**Rename profile: China mobile MMS**

**Homepage : <http://mmsc.monternet.com>**

**Data Account : Choose account under WAP settings: CHINA MOBILE GPRS**

**Connection Type : HTTP**

**Proxy Address : 010.000.000.172**

**Proxy Port : 80**

**If you have any problems in settings, please contact your next service station thru the Website or eMail to: [support@neoi.de](mailto:support@neoi.de) or consult the Website of the concerned Carrier.**

**Neoi 809 Serie Anweisung fuer GPRS , MMS , WAP Settings**

- 1.) Bitte zunaechst feststellen ob die SIM Karte des Service Providers ( z.b. T-Mobile, D2 ) mit einem GPRS Konto ausgeruestet ist, nicht jeder SIM Vertrag hat auch ein GPRS Daten Konto ( haengt vom Service Vertrag ab)
- 2.) SIM Karte Einlegen, Battery einlegen, Geraet einschalten.
- 3.) Zunaechst einen Telefon Anruf machen, dann ein SMS versenden, und feststellen ob beides richtig ausgefuehrt wird.
- 4.) Dann..
  - a.) Menu....
  - b.) Services... Enter ( 5 weg Taste in der Mitte Druecken)
  - c.) Service Menu erscheint bitte feststellen ob das folgende auf dem Bildschirm zu lesen ist:
    - 1 ( Name der SIM Karte , z.b. T-Mobile)
    - 2 WAP
    - 3 Data Account
  - d.) Auf 1 gehen .. Enter ... Es muss nun das Menue des Service Providers angezeigt werden
  - e.) Auf diesem Menu .... Enter .... Nun muessen alle Services des Providers angezeigt werden ( eine lange Liste). Erscheint diese, dann zunaechst einen Service ausprobieren.... wenn das funktioniert, dann ist der GSM Daten Fluss in ordnung and man kann das GPRS Daten Konto programmieren
  - f.) ..... zurueck zu Services
  - g.) 3 (Data Account) waehlen und ENTER
  - h.) 2 GPRS waehlen und ENTER....
  - i.) Neues Account waehlen ( z.b Account 1)...
    - a.) (1) Account Name eintragen ( z.b. T-mobile... bitte bei Service Provider erfragen wie das GPRS Account GENAU heist, ist SEHR wichtig, dad as Geraet spaeter sonst das Account nicht finden kann ueber den eingebauten Browser ! )
    - b.) (2) APN .... Access Point waehlen und eintragen ( auch diese rist vom Service provider zu erfahren
    - c.) (3) User Name waehlen und eintragen ( wird vom Service Provider gegeben, kann auch manchmal blank sein)
    - d.) (4) Password eintragen
    - e.) (5) Auth. Type = Normal
  - j.) BACK Taste Druecken , (2) WAP ... ENTER ...
    - a.) (1) Homepage ....ENTER , es sollte nun die Homepage des Service Providers erscheinen, dann ist das GPRS korrekt programmiert
    - b.) Back....
    - c.) Back....

**Sie sind im Haupt Menu**

- 5.) Gehen Sie zu MESSAGES .... ENTER
- 6.) Gehen Sie zu (2) MMS
- 7.) Gehen Sie zu (6) Message Settings

- a.) Gehen Sie zu (5) Server Profile ... ENTER
  - b.) Waehlen Sie ein neues Profil ( z.b. Profil 2)
  - c.) Gehen Sie zu (2) Edit Profil ... ENTER
  - d.) (1) Den richtigen Profil Namen einsetzen (z.b. mmsc)
  - e.) (2) Die richtige Homepage des MMS Service Providers eintragen
  - f.) (3) Das GPRS Konto welches Sie vorher programmiert haben waehlen
  - g.) (4) Connection Type WAP waehlen
  - h.) (5) User Name ( Benutzer Name) wie vom Service Provider angewiesen eintragen
  - i.) (6) Passwort eintragen
- 8.) Dann BACK.....
  - 9.) (1) Activate Profile ....ENTER
  - 10.) Korrektes Profil waehlen ... ENTER
  - 11.) Back.... Back.... Back..... Back.... zur telefon Screen

Es sollte nun alles programmiert sein. Das Gerat benutzt das Linux Profil, welches sehr einfach zu programmieren ist, da man im Gegensatz zu Windows nur sehr wenige Informationen benoetigt welche vom Service Provider gegeben werden.

Hier im Anhang zum Beispiel die Informationen die man von T-Mobile bekommt, von denen man dann nur einige wenige benutzt.

Es ist leider bekannt, dass Service Providers sogenannte Service Centers wenig Hilfe fuer Kunden geben die das Gerat nicht beim ihm gekauft haben, und immer sagen „Sie kennen das Gerat nicht“. Leider sind diese „Spezialisten“ ueberhaupt nicht ausgebildet. Aber.....

Man kann sehr leicht alle Einstellungen usw. Ueber das Internet finden.

z.b. <http://www.google.de> ..... Dann suchen nach - t-mobile gprs wap einstellungen „ ..... Beispiel Ergebnis siehe unten ...

## Konfiguration

Voraussetzung für die Nutzung der t-zones Dienste sind WAP- bzw. GPRS-Handys/PDA mit eingebautem Micro-Browser, konfiguriert für t-zones.

Sollte Ihr Handy oder PDA nicht bereits vorkonfiguriert sein, dann können Sie es automatisch für t-zones einrichten lassen. Wählen Sie im Konfigurations-Center einfach Ihr Handymodell aus und schon geht's los! ... [zur automatischen Konfiguration](#)

Ist Ihr Handy nicht im Konfigurations-Center verfügbar, halten wir für Sie auch Bedienungsanleitungen bereit, womit Sie Ihr Handy Schritt für Schritt für t-zones einrichten können. ... [zu den Konfigurationsanleitungen](#)

Eine Übersicht der möglichen Konfigurationsdaten finden Sie nachfolgend:

#### GPRS-Verbindung

	WAP	PDA
Verbindungsname:	DE GPRS WAP	DE GPRS WAP
Homepage:	<a href="http://www.t-zones.de">http://www.t-zones.de</a>	<a href="http://www.t-zones.de">http://www.t-zones.de</a>
IP Adresse:	193.254.160.002	193.254.160.001
Passwort abfragen:	Nein	Nein
Datenträger:	GPRS	GPRS
Benutzername:	t-d1	t-d1
Passwort:	wap	wap
Name des Zugangspunktes:	wap.t-d1.de	internet.t-mobile
Authentifizierung:	Normal	Normal
Verbindungs-Sicherheit:	Nein	Nein
Session-Mode:	Permanent	Permanent

#### CSD-Verbindung

	WAP	PDA
Verbindungsname:	DE CSD	DE CSD
Homepage:	<a href="http://www.t-zones.de">http://www.t-zones.de</a>	<a href="http://www.t-zones.de">http://www.t-zones.de</a>
IP Adresse:	193.254.160.002	193.254.160.002
Passwort abfragen:	Nein	Nein
Datenträger:	GSM Data	GSM Data
Telefonnummer:	+491712524120	+491712524120
Benutzername:	t-d1	t-d1
Passwort:	wap	wap
Authentifizierung:	Normal	Normal
Verbindungs-Sicherheit:	Nein	Nein
Session-Mode:	Permanent	Permanent
Ruf-Typ:	Analog	ISDN
Geschwindigkeit:	9600	9600

#### MMS

	Einstellungen
--	---------------

<b>Profilname:</b>	<b>T-D1 MMS</b>
<b>Verbindungs-URL:</b>	<b>http://mms.t-mobile.de/servlets/mms</b>
<b>Sicherheit:</b>	<b>Nein</b>
<b>IP Adresse:</b>	<b>193.254.160.003 &gt; Port hierbei: 9201</b>
<b>Benutzername:</b>	<b>t-d1</b>
<b>Passwort:</b>	<b>mms</b>
<b>Name des Zugangspunktes:</b>	<b>mms.t-d1.de</b>
<b>Proxyserver:</b>	<b>172.028.023.131 &gt; Proxyport hierbei: 8008</b>

## WAP 2

	<b>Einstellungen</b>
<b>Profilname:</b>	<b>DE WAP 2.0</b>
<b>Verbindungs-URL:</b>	<b>http://wap.t-d1.de</b>
<b>Datenträger:</b>	<b>GPRS</b>
<b>Benutzername:</b>	<b>t-mobile</b>
<b>Passwort:</b>	<b>t-d1</b>
<b>Name des Zugangspunktes:</b>	<b>internet.t-mobile</b>
<b>Authentifizierung:</b>	<b>Normal</b>
<b>Login Typ:</b>	<b>Automatisch</b>

**Fuer weitere Informationen gehen Sie bitte zur Webseite**  
<http://www.neoi.de>

